

CUSTOMER SERVICE BULLETIN

Radio Shack® CUSTOMER SERVICE BULLETIN

400 Atrium—One Tandy Center, Fort Worth, Texas 76102

| | |
|--------------|---------------------|
| Bulletin No. | 4515-Ø1 |
| Description | PROFILE PLUS |
| Model | Model II |
| Stock No. | 26-4515 Version 1.Ø |
| Date | Sept. 13, 1982 |
| Page 1 of | 1 |

Problem

In the SELECT/BAS Basic program provided on the Profile Plus master, if a comma is in the text that is being selected, everything after the comma is out of order.

* * THE FOLLOWING LINE CHANGES ARE REQUIRED! * *

Solution

The problem is corrected by following the steps listed below.

1. Backup the diskette(s) and make the changes on the Backup copy of the program.
2. In BASIC load the program by typing LOAD"SELECT/BAS".
3. Make the following corrections:

CHANGES (Retype the line or refer to the Edit section of the owners manual)

Old Line: 8Ø INPUT #1,A\$:IF LEN(A\$)=Ø THEN GOTO 1ØØ

New Line: 8Ø LINE INPUT #1,A\$:IF LEN(A\$)=Ø THEN GOTO 1ØØ

Old Line: 14Ø IF EOF(1) THEN CLOSE:END ELSE INPUT#1,A\$:IF LEN(A\$)>
1 THEN A\$=MID\$(A\$,2,LEN(A\$)-2)

New Line: 14Ø IF EOF(1) THEN CLOSE:END ELSE LINE INPUT#1,A\$:IF LEN(A\$)>
1 THEN A\$=MID\$(A\$,2,LEN(A\$)-2)New Line:

4. Type SAVE"SELECT/BAS" to save the changes in the program.
5. At TRSDOS READY, make a backup copy of the corrected diskette.