

CUSTOMER SERVICE BULLETIN

Radio Shack® CUSTOMER SERVICE BULLETIN

400 Atrium—One Tandy Center, Fort Worth, Texas 76102

Bulletin No.	4531-11
Description	SCRIPSIT
Model	Model II
Stock No.	26-4531 Version 2.0
Date	June 10, 1982
Page 1 of	1

Problem

- 1) Scripsit locks up when the user attempts to use a serial printer with Merge.
- 2) Under some circumstances, when the user recalls text into a word, causing the text to exceed the margins, the cursor may be left off text. Scripsit fails to flag the error and unpredictable results may occur.

Solution

- 1) These patches will correct problem #1.
The date at the bottom of the STARTUP screen must be 06/02/1982 before these patches are applied, if not, obtain and apply all previous patches.

```
PATCH SCRIPSIT/SYS {R=176 B=20 F=90DA C=0BD6}  
PATCH SCRIPSIT {A=D60B F=0000000000000000 C=FD7F7EC8C390DA}
```

- 2) These patches will correct problem #2.

```
PATCH SCRIPSIT {A=B228 F=2CA4 C=DFD5}  
PATCH SCRIPSIT {A=D5DF F=0000000000000000 C=CD2CA4C35CA9}  
PATCH SCRIPSIT {A=B21C F=FE8D20 C=C3B8D5}  
PATCH SCRIPSIT {A=D5B8 F=000000000000000000000000 C=FE8DCA20B2CD5CA9AFC9}
```

After the preceding patches have been applied, make the following patch to change the date at the bottom of the startup screen to 06/09/1982.

```
PATCH STARTUP {A=E412 F=B2 C=B9}
```