

CUSTOMER SERVICE BULLETIN

Radio Shack® CUSTOMER SERVICE BULLETIN

400 Atrium—One Tandy Center, Fort Worth, Texas 76102

Bulletin No.	4912-07
Description	TRSDOS II
Model	Model II/12
Stock No.	26-4912 Ver. 04.02.04
Date	September 26, 1983
Page 1 of	1

Problem

"TERMINAL" patches are shown to permanently change the operation of the Terminal program to use Channel B in place of channel A. These patches should not be applied unless there is a special situation that requires the use of Channel B. Please note that a serial printer (which uses channel B) may not be used concurrently with TERMINAL once the patches have been applied.

* * THE FOLLOWING PATCHES ARE OPTIONAL! * *

Solution

PATCH TERMINAL R=5 B=109 F=3E61 C=3E63
PATCH TERMINAL R=5 B=185 F=3E60 C=3E62
PATCH TERMINAL R=6 B=101 F=3E64 C=3E65
PATCH TERMINAL R=6 B=110 F=3E64 C=3E65
PATCH TERMINAL R=6 B=120 F=3E64 C=3E65
PATCH TERMINAL R=6 B=130 F=3E61 C=3E63
PATCH TERMINAL R=6 B=188 F=3E60 C=3E62
PATCH TERMINAL R=7 B=230 F=3E60 C=3E62
PATCH TERMINAL R=8 B=24 F=3E60 C=3E62

If these optional patches are applied, please make a notation of it on your version log. The Version number remains 04.02.04 after application of the series of patches.