

CUSTOMER SERVICE BULLETIN

Radio Shack® CUSTOMER SERVICE BULLETIN

400 Atrium—One Tandy Center, Fort Worth, Texas 76102

Bulletin No.	6105-10
Description	TRSDOS 16
Model	Model II/16
Stock No.	26-6105 Version 4.1
Date	September 30, 1982
Page 1 of	1

Problem

BACKUP will make a floppy disk unusable when a single drive backup is done. This is accomplished by, BACKUP 0 0 or similar method. The correct error messages are given but the disk is modified anyway.

The patches below will still give the correct error messages, but will prevent the disk from being modified.

* * THE FOLLOWING PATCHES ARE REQUIRED! * *

Solution

1. At TRSDOS Ready, apply the following patches to correct the problem.

```
PATCH BACKUP R=1 B=65 F=41 C=4D
PATCH BACKUP R=1 B=71 F=41 C=4D
PATCH BACKUP R=1 B=77 F=41 C=4D
PATCH BACKUP R=2 B=113 F=217F321803217032CD672C21
C=216733010001CDAA2CCD952B
PATCH BACKUP R=2 B=125 F=6733010001CDAA2CCD952B
C=217F321803217032CD672C
```

2. Make a backup copy of the patched diskette.